

Gas meter

Combustible Gas Detector

Model: 822M



Specifications

Model	822M
Sensor	Gas-sensitive semi-conductor
Range	50-1000PPM(Methane)
Reactions sensitivity	<50ppm(methane)
Warm-up time	30s
Response time	<500PPM: 5s >500PPM: 2s
Storage condition	-10 to 60C,20%- 80%RH
Operation condition	-0 to 50C, 20%-80%RH

Features

Model	822M
Low battery indication	√
Auto power off	√
Alarm	Audio + light

General Information

Model	822M
Power supply	1.5V AAA x 2
Product size	250*36*20mm
Product weight	100g
Standard accessories	Manual, batteries